

## Push Dimming




Reset Switch

- On/off control: Short press.
- Stepless dimming: Long press.
- With every other long press, the light level goes to the opposite direction.
- Dimming memory: Brightness will be the same as previously adjusted when turning off and on again.

## LED Current Selection

The current can be easily configured by choosing the correct combination of the DIP switches [see the table below].



⬇ ⬇ ⬇	⬇ ⬆ ⬆	⬆ ⬆ ⬆	⬆ ⬆ ⬆	⬆ ⬆ ⬆	⬆ ⬆ ⬆	⬆ ⬆ ⬆	⬆ ⬆ ⬆	⬆ ⬆ ⬆	⬆ ⬆	⬆
100mA/ISET	120mA	150mA	200mA	250mA	300mA	350mA	400mA	ON	OFF	
3-54V	3-54V	3-54V	3-54V	3-54V	3-50V	3-36V	3-36V			

\* After current setting by DIP switch, power off and then power on to make the new current effective.

\* E.g. LED 3.2V/pcs: 3-54V can power 1-16pcs LEDs in series, 3-36V can power 1-11pcs LEDs, the max quantity of LEDs in series will be subject to the actual voltage of LED.